

EC45 Mixer



SKU:

EAN:

FEATUES

- Provide 8/12/16 inputs, 1*5 segment LED level signal indicator per channel, built-in digital effects, DSP algorithm, 99 programming, PARAMETER controller, USB audio, 2IN/2OUT: USB2.0 compatible, dual-track recording
 - Lossless USB music player, supports decoding formats: WAV, WMA, APE, FLAC, MP3, supports SD card, multi-track recording, dual-channel headphone monitoring, connects to a variety of devices for different occasions, powerful and rich compatibility, can connect to a variety of audio devices, easy to use
 - Multiple occasions, easy to deal with
- Designed for wedding stages, performances, conferences, banquet halls, gymnasiums, bar halls, etc.



SPECIFICATION

Provide 8/12/16 inputs

8 mono, 2 stereo

The PAD attenuation is -20dB

3-band UK EQ

HIGH: Gain: +15 dB/-15dB, Frequency: 12kHz slope

MID: Gain: +15dB/-15dB, Frequency: 4kHz peak

LOW: Gain: +15dB/-15dB, Frequency: 80Hz slope

1*5 segments of LED level signal indicator per channel

2*12 Dot-Pitch LED Level Meter, LEVEL:[-36,-30,-24,-18,-12,-6,-3,0,+3,+6,+10,+20dB]

BUILT-IN DIGITAL EFFECTS, DSP ALGORITHMS, 99 KINDS OF PROGRAMMING, PARAMETER CONTROLLER

USB Audio, 2IN/2OUT

USB2.0 compatible, dual-track recording

Phantom power

voltage +48V, each channel is independently controlled

Lossless USB music player, support decoding formats

WAV, WMA, APE, FLAC, MP3, support SD card, multi-track recording

Dual-channel headphone monitoring

2 sets of AUX SEND auxiliary outputs

Each independent REC multi-track recording control knob

1 set of TRTURN return function inputs

1 pin RCA stereo input

1 set of needle RCA stereo recording outputs

2GROUP OUT: group output

Dual-channel MAIN OUT stereo output

HIGHLY RELIABLE, SMOOTH 60MM TRAVEL FADERS